

ZTPA-350W6Z

Mixer Amplifier with USB & Tuner



Features

- 100V & 4-16 Ω , rated power 350W
- Support USB / SD / FM radio, with built-in chime
- 4 MIC inputs, Mic 1 with priority and muting fun
- 3 AUX line input & 1 AUX line output for power extension
- Each AUX & Mic input with individual volume

Description

This mixing amplifier is rated at 350W. 100V and 4-16 Ω speaker output are provided. There are 3 unbalanced microphones inputs and 3 aux inputs. Bass and treble controls and master volume control are provided. This amplifier can be applied to different occasions, such as supermarket, classroom, etc. Extensive protection from short-circuit, overload and high temp is ensured. Automatic cooling system ensures the extreme quite sound system.

Specification

Model	ZTPA-350W6Z
Rated Output	350W
Output Regulation	Less than 3dB, from off-load to full load
Input sensitivity	MIC: 3.0mV(±0.5mV)
	LINE: 300mV(±50mV)
Frequency Response	80Hz-16kHz
Distortion	Less than 1% (at 1kHz, 1/3 rated output voltage)
Ratio of Signal to Noise	MIC: more than 71dB
	LINE: more than 85dB
Tone	Bass: ±10dB (at 100Hz)
	Treble: ±10dB (at 10kHz)
Protection	DC voltage; overload; short-circuit.
Mute	Input signals from MIC 1 override other input signals
Power Requirements	AC 220-240V/50-60Hz
Power Consumption	650W
Outer Packing Size(mm)	(L×W×H)520×430×195
Unit Size (mm)	(L×W×H)418×355×88
Gross Weight	17kg
Net Weight	15kg

