

ZTPA-6022D

Mixer Amplifier



Features

- **Dual-Zone Control:** 2 zones mini mixer amplifier for versatile audio routing and distribution.
- **Modern Connectivity:** Built-in Bluetooth, FM radio, USB, and SD card ports for seamless media playback.
- **Flexible Inputs:** Features 2 MIC inputs and 1 AUX input to accommodate multiple audio sources.
- **Customizable Audio:** Independent treble and bass adjustment controls to fine-tune sound output.
- **Reliable Design:** Bottom heat dissipation design ensures stable operation during continuous use.
- **Comprehensive Protection:** Built-in safety features including DC, Overload, Short Circuit, and Soft-start protection

Description

The Mini Mixer Amplifier M-F60 is a compact, versatile, and highly efficient audio solution designed for small to medium-sized public address (PA) and background music systems. Delivering a reliable 60W of rated power, this 2-zone amplifier provides exceptional sound clarity and ease of use.

It comes fully equipped with modern multimedia connectivity—including built-in Bluetooth, USB, SD Card, and FM radio—making it an ideal choice for Classes, retail stores, clinics, and small offices..

Specification

Model	ZTPA-6022D
Rated Output	60W
Power Supply	AC 100V-240V / 50HZ
Frequency Response	20Hz - 30KHz
Input Sensitivity	550mv
Input Impedance	10kΩ / 20kΩ
Output Impedance	4-8-16Ω
T.H.D (Total Harmonic Distortion)	0.1%
S.N.R (Signal-to-Noise Ratio)	85dB
Protection	DC voltage; overload; short-circuit.
Inputs	2MIC input,1 AUX input With treble and bass adjustment
Interace	Bluetooth, FM, USB,SD card port
Unit Size (mm)	300×73×190
Net Weight	2kg

